



GroundControl Multi v3 Main DMX Map

Channel	Function	Description	8-Bit	16-Bit	DMX Percent
1	CONTROLLER CONFIGURATION	Controller mechanism selection	Home: 0		0%
		Refer to "GroundControl Controller Mechanism"	0-255		
2	CAMERA EXPOSURE	Camera exposure control	Home: 0		0%
		No change			
3	CAMERA ZOOM	Camera zoom control	Home: 0		0%
		No change	0		
		Wide	1		
		Narrow	255		
4	CAMERA WB + RETICLE	Camera white balance + reticle	Home: 0		0%
		No Change	0		0%
		Automatic	1		1%
		3200K	2		1%
		5800K	3		2%
		ATW	4		2%
		One-Push WB	5		2%
		Reticle Off	127		49%
		Reticle On	128		50%
5	CONTROL SELECTION	Console or GC control selection	home: 0		0%
		Idle	0		0%
		Console Control	1		1%
		GC Control	10		3%
6	STORE TARGET POINTS	Target point storing	home: 0		0%
		Idle	0		0%
		Store Target Point Alpha	56		21%
		Store Target Point Bravo	58		22%
		Store Target Point Charlie	60		23%
		Store Target Point Delta	62		24%
		Store Target Point Echo	64		25%
		Store Target Point Foxtrot	66		26%
		Store Target Point Golf	68		27%
		Store Target Point Hotel	70		27%
		Store Target Point India	72		28%
		Store Target Point Juliett	74		29%
7	RESERVED		home: 0		0%

GC Multi v3 Main DMX Map

Followspot Controller Mechanism Selection

The “Controller Mechanism Select” channel allows Remote Followspot Controller mechanisms to be selected as follows:

DMX Range	Mech 1	Mech 2	Mech 3	Mech 4	Mech 5
0	No Change (leave mechanisms as they are)				
1-5 (default)	Intensity	Iris	Edge	Zoom	Frost
6-10	Intensity	Iris	Edge	Zoom	
11-15	Intensity	Iris	Edge		
16-20	Intensity	Iris		Zoom	Frost
21-25	Intensity	Iris		Zoom	
26-30	Intensity	Iris			Frost
31-35	Intensity	Iris			
36-40	Intensity				
41-45	Intensity		Edge	Zoom	Frost
46-50	Intensity		Edge	Zoom	
51-55	Intensity		Edge		
56-60	Intensity			Zoom	Frost
61-65	Intensity			Zoom	
66-70	Intensity				Frost
71-75		Iris	Edge	Zoom	Frost
76-80		Iris	Edge	Zoom	
81-85		Iris	Edge		
86-90		Iris		Zoom	Frost
91-95		Iris		Zoom	
96-100		Iris			Frost
101-105		Iris			
106-110			Edge	Zoom	Frost
111-115			Edge	Zoom	
116-120			Edge		
121-125				Zoom	Frost
126-130				Zoom	
131-135					Frost
136-140	Console controls all FSC mechanisms EXCEPT Pan & Tilt				